



Wattstopper
Vacancy Sensor, 3-wire w/Nightlight, White
Part No. RS-150BA-N-W



The RS-150BA-N Passive Infrared (PIR) Vacancy Sensor provides automatic shutoff for single-pole lighting control applications. It is engineered to comply with specific provisions of California's Title 24-2013 energy code.

Features & Benefits

Complies with 2011 NEC requirements	Integral LED nightlight
Relay-based switching	Replaces single-pole switches
Fixed 30-minute time delay; no adjustment necessary	Amber LED nightlight illuminates whenever connected load is off
Low-profile styling	Choice of five decorator colors; lens is color-matched to device
Manual-on/automatic-off control	Ideal for bathrooms
Integral LED nightlight	Fixed 30-minute time delay

Specifications

General Info

Product Line	Wattstopper	Color	White
UPC Number	754182917280	Country Of Origin	China
Features	IR (Infrared), Motion Sensor, Nightlight	Switch Type	Motion Sensor
Application Sector	Commercial	Warranty Type	5-Year

Dimensions

Product Width US	4.0 in	Product Weight US	0.3 lb
Product Volume US	63.0 cu in	Product Depth US	5.0 in
Product Height US	3.15 in		

Additional Information

RoHS Conformant	Yes	DesignLights Consortium Qualified System	Yes
-----------------	-----	--	-----

Security	Yes
----------	-----

Technical Information

Response Frequency	60 Hz	Sensor Type	Vacancy
--------------------	-------	-------------	---------

Number of Buttons	1	Amperage	5 A
-------------------	---	----------	-----

Indicator	LED Light	Wattage	600 W
-----------	-----------	---------	-------

Sensing Range	600 sq ft, 180 degrees	Voltage	120.0 V
---------------	------------------------	---------	---------

Connection Type	Wired
-----------------	-------
