



The PW-301 passive infrared (PIR) wall switch sensor can turn lights OFF and ON based on occupancy.

## Features & Benefits

Color-matched lens and low profile for appealing design	Optional neutral connection with break off tab to expose neutral terminals
120/240/277 VAC and 347 VAC models	Allows multi-way control from one of up to four control locations
High sensitivity and dense coverage for exceptional performance	Defaults to Manual-ON operation for maximum energy savings

## Specifications

### General Info

Product Line	Pass & Seymour	Country Of Origin	China
Features	IR (Infrared), Motion Sensor	Switch Type	Motion Sensor
Application Sector	Commercial		

### Dimensions

Product Width US	1.75 in	Product Depth US	1.81 in
Product Height US	2.73 in	Product Length US	2.73 in

### Technical Information

Response Frequency	60 Hz	Sensor Type	Occupancy
Number of Buttons	1	Indoor/Outdoor	Indoor
Wattage	1200 W	Mounting Type	Box
Sensing Range	180 degrees,1050 sq ft	Voltage	120/277 V
Connection Type	Wired	Load	1000W