



The RS-250 Passive Infrared (PIR) Occupancy Sensor provides automatic lighting shutoff for single-pole lighting control applications.

## Features & Benefits

|   |  |
|---|--|
| Lighted switch for visibility in darkened rooms                 | Fixed five-minute time delay                                       |
| Low-profile styling with uniform, color-matched lens and device | With the RS-150U option, no leakage to load in off mode for safety |
| Replaces standard light or fan single-pole switches             | Automatic-on operation   |

## Specifications

### General Info

|                    |   |                   |               |
|--------------------|---|-------------------|---------------|
| Product Line       | Pass & Seymour                              | Country Of Origin | China         |
| Features           | IR (Infrared), Locator Light, Motion Sensor | Switch Type       | Motion Sensor |
| Application Sector | Residential                                 | Warranty Type     | 5-Year        |

### Dimensions

|                   |         |                   |         |
|-------------------|---------|-------------------|---------|
| Product Width US  | 1.69 in | Product Depth US  | 1.88 in |
| Product Height US | 2.63 in | Product Length US | 2.63 in |

### Technical Information

|                    |         |                 |                                    |
|--------------------|---------|-----------------|------------------------------------|
| Response Frequency | 60 Hz   | Sensor Type     | Occupancy                          |
| Number of Buttons  | 1       | Number of Poles | Single Pole                        |
| Indoor/Outdoor     | Indoor  | Wattage         | 600 W                              |
| Mounting Type      | Box     | Sensing Range   | 180 degrees, 12 x 25 ft, 600 sq ft |
| Voltage            | 120.0 V | Connection Type | Wired                              |
| Load               | 600W    |                 |                                    |